

## Coaxial Cable Preparation Tool Kit LMR195/240/400

## **CK2500**



## The CK2500 Coaxial Cable Preparation Tool Kit contains:

- 1 x Ratchet Crimp Tool with 5 interchangeable hex dies for RG/LMR Cables (0.042"/1.07mm to 0.429"/10.9mm)
- 1 x Cable Cutter with curved blade for cables up to 10.5mm diameter
- 1 x Rotary Coax Cable Stripper with adjustable blades
- 1 x Screwdriver for changing crimp dies
- 1 x Plastic carry case

## Die Sizes

$\bigcirc$	$\bigcirc$	$\bigcirc$	$\bigcirc$	O PIN	SQ. PIN	For Crimping RG & LMR Cables
	.255* 6.5mm	.213" 5.41mm	.187" 4.75mm	.068" 1.72mm		55,58, 59, 62, 140, 141, 142, 174, 210, 223, 303, 400, LMR100, 195, 200, 240 Fibre Optic, Belen 8279
.319" 8.1mm	.256" 6.5mm	.213" 5.41mm		.068" 1.72mm		55,58, 59, 62, 140, 141, 142, 174, 210, 223, 303, 400, LMR195, 200, 240 Fibre Optic, Belen 8279
.255" 6.48mm	.213" 5.41mm	.137" 3.50mm	.100" 2.54mm	.069" 1.75mm	.043" 1.07mm	59, 62, 8X, 140, 210, Belden 8279 55, 58, 141, 142, 174, 223, 303, 400, Fibre Optic
.178" 4.52mm	.151* 3.84mm	.128" 3.25mm	.078" 2.00mm	.068" 1.72mm	.042" 1.07mm	122, 174, 179, 180, 187, 188, 195, Fibre Optic 178, 316, Belden 8218
.429" 10.9mm		.128" 3.25mm	.100" 2.54mm			8, 9, 11, 87A, 149, 165, 213, 214, 216, 225, 393 & LMR400*, 339, 174, 179, 187, 188, 316, LMR100



Email: sales@comnet.com.au
Website: www.comnet.com.au
Telephone: +61 2 9899 5700

Comnet Solutions 19/9 Hoyle Avenue Castle Hill NSW 2154 Australia